



F&F Filipowski sp. j.
Konstantynowska 79/81 95-200 Pabianice
phone/fax: (+48 42) 215 23 83 / 227 09 71 POLAND
http://www.fif.com.pl e-mail: fif@fif.com.pl

PULSE POWER SUPPLY
Stabilized

ZI-21

WARRANTY. The F&F products are covered by a warranty of the 24 months from the date of purchase. Effective only with proof of purchase. Contact your dealer or directly with us. More information how to make a complaint can be found on the website:
www.fif.com.pl/reklamacje



Do not dispose of this device to a garbage bin with other unsorted waste!
In accordance with the Waste Electrical and Electronic Equipment Act any household electro-waste can be turned in free of charge and in any quantity to a collection point established for this purpose, as well as to the store in the event of purchasing new equipment (as per the old for new rule, regardless of brand). Electro-waste thrown in the garbage bin or abandoned in the bosom of nature pose a threat to the environment and human health.

Purpose

Pulse power supply is used for powering electrical and electronic equipment that require stable, filtered supply voltage independent of mains voltage alterations.

Mounting


1. Turn off the power.
2. Connect network cables to the input terminals 1-3 of the power supply.
3. Connect the receiver to the output terminals of the power supply in accordance with the marked polarization 10 (+) - 12 (-).

- 1 -

Technical data

input voltage	100-264V AC
output voltage	24V DC
output current	0.5A
power output	12W
current limit	$I_{max}=110\%I_{out}$
minimum load	0%
keying frequency	70kHz
working temperature	-10-40°C
terminal	2.5mm ² screw terminals
dimensions	1 module (18mm)
weight	80g
mounting	on TH-35 rail
ingress protection	IP20

Wiring diagram



D150924

- 2 -