



ul. Konstytucyjna 79/81
95-200 Pabianice
tel/fax 48 42 2270971 POLAND
e-mail: fif@fif.com.pl

PSI-02 230V
SIGNAL CONVERTER
continuous ->pulse



519 0 8 3 1 2 1 5 9 1 5 9 7

www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase

PURPOSE

The PSI-02 converter serves to break up a control signal into single pulses required in automatic control systems.

FUNCTIONING

After the application of the control signal to the U_{st} input (leading edge), the converter generates a pulse on output 12 (contact 11-12 closed for 1 second). After the decay of the control signal (trailing edge), the converter sends another pulse on output 9 (joint 8-9 closed for 1 second).




ASSEMBLY

1. Take OFF the power.
2. Put on the converter on the rail in the switchgearbox
3. Power supply connect to joints 1-3.
4. To input 6 connect controlling cable.
5. To joints 11-12 connect circuit which is control by first pulse.
6. To joints 8-9 connect circuit which is control by second pulse.

TECHNICAL DATA

supply	230V AC
current load	2× [$<8A$]
joint	2× separate 1P
control voltage	230V AC
time of input signals	1sec
working temperature	-25+50°C
connection	screw terminals 2,5mm ²
dimensions	1 module (18mm)
fixing	on rail TH-35

WIRING DIAGRAM



A090805