

F&F Filipowski sp. j. Konstantynowska 79/81, 95-200 Pabianice, POLAND phone/fax (+48 42) 215 23 83 / (+48 42) 227 09 71 www.fif.com.pl; e-mail: biuro@fif.com.pl

# BIS-408

Bistable relay



Do not dispose of this device in the trash along with other waste!

According to the Law on Waste, electro coming from households free of charge and can
give any amount to up to that end point of collections, as well as to stone the occasion of
the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction of the contraction



# Purpose

Electronic bistable pulse relay BIS-408 allows switching on or off the lighting or other device from several different points by parallel connected, momentary (bell) control switches.

#### Functioning

The receiver is switched on after a current pulse caused by pressing any momentary (bell) button connected to the relay.

The receiver is turned off after the next impulse.


The relay does not have a "memory" of the contact position, which means in the event of a power failure and its subsequent return, the relay contact will be set to "off".

This prevents the controlled receivers from being switched on automatically without supervision after a prolonged power failure.

#### Mounting

- 1. Disconnect the power supply.
- 2. Mount relay in the flush-mounted box.
- 3.Connect the power supply cables to PWR group: phase L-wire to terminal 5 or 6 and neutral N-wire to terminal 3 or 4.
- 4. Momentary switches connected in parallel connect to terminal 1 and phase L-wire.
- Connect the powered receiver in series to terminal 2 and neutral N-wire.

# Wiring diagram



- 1 control input
- 2 relay output
- 3/4 N power supply
- 5/6 L power supply



## BIS-408 is compatible with backlit buttons.




The maximum total backlight current of all connected buttons must not exceed 5 mA.

# Technical data

power supply	165÷265 V AC
contact	1×NO
maximum load current (AC-1)	16 A
control pulse current	5 mA
activation delay	0.1÷0.2 s
switch-off time (adjustable)	1÷15 min.
power indication	green LED
power consumption	
standby	0.15 W
on	0.7 W
terminal	2.5 mm <sup>2</sup> screw terminals
tightening torque	0.4 Nm
working temperature	-25÷50°C
dimensions	ø54 (size 48×43 mm), h= 25 mm
mounting	in flush mounted box Ø60
ingress protection	IP20

## Power table



The above data are indicative and will heavily depend on the design of a specific receiver (that is especially important for LED bulbs, energy-saving lamps, electronic transformers and pulse power supply units), switching frequency and operating conditions.

For more information visit: www.fif.com.pl.

#### Warranty

The F&F products are covered by a warranty of the 24 months from the date of purchase. Effective only with proof of purchase. Contact your dealer or directly with us.

#### CE declaration

F&F Filipowski sp. j. declares that the device is in conformity with the essential requirements of The Low Voltage Directive (LVD) 2014/35/EU and the Electromagnetic Compatibility (EMC) Directive 2014/30/UE.

The CE Declaration of Conformity, along with the references to the standards in relation to which conformity is declared, can be found at <a href="www.fif.com.pl">www.fif.com.pl</a> on the product page.

E211130 - 4 -