



ul. Konstytucyjna 79/81
95-200 Pabianice
tel/fax 48 42 2270971 POLAND
e-mail: fif@fif.com.pl

CP-730 VOLTAGE RELAYS three-phase type




www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase

PURPOSE

Voltage relays CP-30 serves to voltage control in three phase mains and to protect receiver against the effects of voltage collapse or increase beyond set values.



ASSEMBLY

1. Take OFF the power.
2. Put on the relay on the rail in the switchgear box .
3. Connect to installation with wiring diagram..
4. Set to voltage thresholds U1 and U2.

TECHNICAL DATA

supply	3x(50+450V)+N
current load	<10A
joint	1P
sygnalling of supply	4xLED
voltage activation treshold	
lower U1	150+210V
upper U2	230+260V
hystereisis	
for U1	5V
for U2	5V
activation time	
for U1	0,5sec
for U2	0,1sec
recovery time	
for U1	1,5sec
for U2	1,5sec
power consumption	0,8W
working temperature	-25+50°C
connection	screw terminals 2,5mm ²
dimensions	3 modules (52,5mm)
fixing	on rail TH-35

FUNCTIONING

Lower voltage value (U1) and upper voltage value (U2) are set by means of potentiometers. It is so-called eye of voltage, in limits of which can occur changes of phases voltages that do not cause activation of relay. Supplied a relay is signalized by shine of green LED .Correct value of voltage is signalized by shine of yellow LED. (position of joint 11-12). Change of phase voltage on one of phases above or below set voltage tresholds will cause activation of relay (switch joints to position 11-10). Decrease of voltage below establish value U1 is signalized by shine of LED red (U1). Increase of voltage below establish value U2 is signalized by shine of LED red (U2). Reactivation follows automatically return of correct voltage value.

ATTENTION!

Because of unstable voltage in mains and frequent changes of supply voltage beyond the set thresholds of "eye of voltage" (at least 10 times per 1minute), relay blocks itself for 10 minutes (joint stay at position 11,-10). This prevents against too frequent, cyclic switching-ON and OFF of the connected receiver. Condition of blockade is signalized by shine of yellow LED.

WIRING DIAGRAM

